

TOKEN®

GASOLINE GENERATOR

EMAXQ1-250A



MODEL		EMAXQ1-250A
Engine	Model	EM460
	Displacement (cm ³)	458
	Ignition system	Transistorized magneto ignition
	Starting system	Recoil / electric
Alternator	Type	Synchronous generator
	Phase	Single phase
	Frequency (Hz)	50
	Rated output (KVA)	5
	Max. output (KVA)	5.5
	Voltage (V)	220
	Power factor	1
Welding	No load voltage (V)	85
	Rated voltage (V)	27.6
	Rated current (A)	190
	Rated duty circle (%)	40
	Current regulation range (A)	50 – 220
	Rated load voltage (V)	22 – 28
	Welding rod diameter (mm)	2.0 – 5.0
Generator	Fuel tank volume (L)	25
	L x W x H (mm)	680 x 530 x 550
	Net weight (kg)	99.5